

OTHER ARTICLES IN THE ANALOG LIGHTNING-FAMILY:

Need to add more external lights to Analog Lightning?

Auxiliary DT-cable (65-3025-DT)

Additional adaptercables

Adapter DT 1x2-pole to 1x3-pole (65-DT1213)

Adapter DT 1x2-pole to 1x4-pole (65-DT1214)

Adapter DT 1x2-pole to 2x2-pole (65-DT1222)

Adapter DT 1x2-pole to 2x3-pole (65-DT1223)

Adapter DT 1x2-pole to 2x4-pole (65-DT1224)

Adapter DT 1x2-pole to 1x2-pole Superseal (65-DT12SS12)

Complete kits

Analog Lightning 3025 Minus (65-3025M)

Analog Lightning 3025 Plus (65-3025P)

Analog Lightning Reverse 2025 Plus (65-2025P)

Spare parts

Electronic controller EB3025 MINUS (65-3025 MINUS)

Electronic controller EB3025 PLUS (65-3025 PLUS)

Electronic controller EB2025 PLUS (SSPS25A)

Modernum AB

visiting/postal address:

Johanneslundsvägen 12, SE-194 61 Upplands Väsby

telephone: +46 8 626 95 00

e-mail: info@modernum.se

web: www.modernum.se



Analog Lightning 3025

A professional kit designed for cars with analog controlled headlights. The Analog Lightning 3025-kit includes an electronic controller together with fused cablings with a DT-connector for an easy connection to a LED light bar or other external lights.

Articles:

Analog Lightning 3025 Plus (for analog plus-signals)

Analog Lightning 3025 Minus (for analog minus-signals)

Technical data:

Rated voltage:	12/24VDC
Output current:	13A (25A without DT-contact)
Current consumption:	2mA
Ambient operating temp.:	-40°C to +85°C
Electronic overheat protection:	+150°C

Note: Analog Lightning comes in two versions; Plus and Minus (analog signal in). Please make sure that you choose the correct version for your vehicle before you start the installation.

* Screw not included

- Terminals on the electronics:
1. + OUT
 2. + OUT
 3. + OUT
 4. + IN 12/24V
 5. + IN 12/24V
 6. - GROUND
 7. ANALOG SIGNAL IN



Note!!!
Mounting direction



Support:
+46 8 626 95 00
info@modernum.se

